



AGM JUMP STARTER

SOSBOOST ⚡ 12/24 V ⚡ 2400/1200 CA



+++

Our AGM batteries, with pure lead are extremely efficient thanks to their ability to deliver energy at high amperage almost instantaneously (cranking amps is what is required to make the vehicle start).

Starting cables (double insulation) with an optimal length and extremely flexible benefit from a high conductivity as well as a perfect shape resistant to frequent handling.

The internal fuse protects the batteries against shortcircuits.

The single-piece moulded case in polyethylene of 5 mm, unbreakable (life time warranty), assures excellent resistance to shocks and everyday uses.



THE SOSBOOST RANGE



SOS 12/24 V
1400/700 CA

12/24 V
1600/800 CA

12/24 V
2000-1000 CA

12/24 V
2400/1200 CA

M 12/24 V
3200/1600 CA

TECHNICAL INFORMATION

MODEL	12/24 V 1400/700 CA	12/24 V 1600/800 CA	12/24 V 2000/1000 CA	12/24 V 2400/1200 CA	M 12/24 V 3200/1600 CA
PART NUMBER	761001	761006	231009	760008	960000
VOLTAGE (DC)	12/24 V	12/24 V	12/24 V	12/24 V	12/24 V
CRANKING AMPS (CA)	1400/700	1600/800	2000/1000	2400/1200	3200/1200
CABLE LENGTH	1,35 m	1,35 m	1,70 m	1,35 m	1,95 m
CABLE CROSS SECTION	35 mm ²	35 mm ²	50 mm ²	50 mm ²	70 mm ²
AUTOMATIC CHARGER	4 A	4 A	4 A	4 A	7 A



PACKAGING INFORMATION

MODEL	12/24 V 1400/700 CA	12/24 V 1600/800 CA	12/24 V 2000/1000 CA	12/24 V 2400/1200 CA	M 12/24 V 3200/1600 CA
NET WEIGHT	20,5 kg	20,5 kg	24,4 kg	24,8 kg	55 kg
DIMENSIONS (L x W x h) mm	530 x 160 x 480	530 x 160 x 480	410 x 225 X 400	530 x 160 x 480	470 x 340 x 970



HOW TO CHOOSE

12 V






24V

PART NUMBER	MODEL	VOLTAGE	<125	150	175	250	300	350	500	100	250	500	1000	1500	2000
			HP* = CHECK YOUR ENGINE HP - LEGEND: ■ NORMAL ■■ INTENSIVE												
761001	12/24 V 1400/700 CA	12/24 V	■■	■■	■■	■■	■	■		■■	■				
761006	12/24 V 1600/800 CA	12/24 V	■■	■■	■■	■■	■■	■		■■	■■	■			
231009	12/24 V 2000/1000 CA	12/24 V	■■	■■	■■	■■	■■	■		■■	■■	■			
760008	12/24 V-2400/1200 CA	12/24 V	■■	■■	■■	■■	■■	■■	■■	■■	■■	■■	■	■	
960000	12/24 V-3200/1600 CA	12/24 V	■■	■■	■■	■■	■■	■■	■■	■■	■■	■■	■■	■	

AUXILIARY CONNECTOR BUILT ON THE BOOSTER

	
Portable 860014	Mobile 860022

OPTIONAL AUXILIARY CABLES

PLUG	PN FOR PORATBLE	PN FOR MOBILE	PLUG	PN FOR PORATBLE	PN FOR MOBILE
	860037	860035		976001	976002
	860016	860034		976003	976004
	860015	860024		860032	860033